



A.H. Systems, Inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311



Tel: (818) 998-0223



sales@AHSystems.com

Fax: (818) 998-6892



www.AHSystems.com

ICP-522

Injection Current Probe

1 MHz – 400 MHz

This injection current probe is used to couple large RF currents from 1 MHz to 400 MHz into signal and power circuits to meet specific testing requirements.



Frequency Range: 1 MHz – 400 MHz

Insertion Loss: 4 to 22 dB

Transfer Impedance: 12 to 33 dBΩ

Rated Watts: 100 watts CW

Connector: N-Type, female

Physical Dimensions

Inner Diameter: 1.6 in. (40 mm)

Outer Diameter: 5.0 in. (127 mm)

Height: 2.0 in. (64 mm)

Weight: 4.0 lb.'s (1.8 kg)

Features

- Measures currents on 50 Hz, 60 Hz and 400 Hz power lines
- Individually Calibrated (Transfer Impedance calibration included)
- Split Type Clamp-on Design

Injection Current Probes are used to inductively couple large RF currents into conductors passing through their aperture. The conductors are signal, control and power circuits of equipment under test for conducted susceptibility or immunity. This injection current probe is used to couple large RF currents from 1 MHz to 400 MHz. The CW input power rating of this injection current probe is 200 watts for a duration of 30 minutes.

Recommended Accessories

- SAC-211 (3 meter N/N Cable, RG-214U)
- CPF-530 Current Probe Fixture
- BCP-520 Monitoring Current Probe



A.H. Systems, Inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311



Tel: (818) 998-0223
Fax: (818) 998-6892

◆ sales@AHSystems.com
◆ www.AHSystems.com



A.H. Systems, inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311
818.998.0223 fax 818.998.6892
info@AHSystems.com www.AHSystems.com



**Injection Current Probe
Insertion Loss
Model: ICP-522**

Insertion Conversion Formula:

$$\text{Injected Current(dB)} = \text{input Current(dB)} - \text{Insertion Loss(dB)} - \text{cable loss}$$

