



A.H. Systems, Inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311



Tel: (818) 998-0223



sales@AHSystems.com

Fax: (818) 998-6892



www.AHSystems.com

SAS-560

Passive Loop Antenna

20 Hz – 2 MHz

This Loop sensor is built in accordance to the MIL-STD 461 specification for low frequency magnetic field testing.



Frequency Range:	20 Hz - 2 MHz
Turns:	36 (<i>7-41 Litz</i>)
Shielding:	Electrostatic
Connector:	BNC, Female

Features

- Low Frequency Range of 20 Hz to 2 MHz
- Individually Calibrated (Calibration included per IEEE-291)
- Rugged Construction
- Three Year Warranty

The SAS-560 passive Loop antenna was built for MIL-STD 461 RE 101 testing. This passive loop antenna has 36 turns enclosed in an electrostatic shielded loop. The loop diameter is 5 1/4" (13.3 cm) and has approximately 10 ohms of DC resistance. The Passive Loop Antenna is an ideal solution for a wide range of magnetic field testing. Whether used in a set to measure shielding effectiveness per MIL-STD 285 and NSA 65-6, or individually to satisfy specific requirements; this Loop Antenna is an efficient, low cost solution.

Recommended Accessories

- SAC-210 (3 meter BNC/BNC Cable, RG-58A/U)
- ADP-202 (BNC(m) to N(f) Adapter)
- ATU-510 (Antenna Tripod Unit, wooden)
- AEH-510 (Azimuth and Elevation Head, Plastic)
- Custom loop tripod stand upon request P/N# 2274



A.H. Systems, Inc.

9710 Cozycroft Ave.
Chatsworth, CA 91311



Tel: (818) 998-0223
Fax: (818) 998-6892


◆ sales@AHSystems.com
◆ www.AHSystems.com



A.H. Systems Inc.

9710 Cozycroft Ave. Chatsworth, CA 91311
Phone (818) 998-0223 Fax (818) 998-6892
E-mail: sales@AHSystems.com
Web site: <http://www.AHSystems.com>

Correction Factor
Model: SAS-560
Loop Sensor



Physical Dimensions

Loop Diameter: 5¼ in. (13.3cm)
Weight: 0.2 lb.'s (0.09 kg)